Application no. 10/027,604
Response and Amendment dated 12/21/2004
in Reply to Office Action dated 09/21/2004

IN THE CLAIMS

1. (currently amended)   A method of displaying an input signal, the method comprising:

sampling the input signal;

searching for a zero space pattern in the sampled signal;

locating a first zero space;

locating a second zero space, following the first zero space;

calculating bit period of the input signal by determining time period between the first zero space and the second zero space; and

displaying the input signal using the calculated bit period as the basis for a scale; and

wherein each of the zero spaces is a period of time with no signal value above a threshold.

2. (original)   The method recited in claim 1 further comprising initializing offset and time scale.

3. (original)   The method recited in claim 1 further comprising determining whether NRZ autoscale is applicable.

4. (original)   The method recited in claim 1 wherein the step of locating the first zero space comprises:

locating a first transition, X_1, where value of the input signal is more than a threshold value, V_{THRES}, before the first transition, X_1, but less than the threshold value, V_{THRES}, after the first transition, X_1, the first transition, X_1, being the first such transition following the offset; and

locating a second transition, X_2, where value of the input signal is less than the threshold value, V_{THRES}, before the second transition, X_2, but more than the threshold value, V_{THRES}, after the second transition, $X2$, the second transition, X_2, being the first such transition following the first transition, X_1.

Application no. 10/027,604
Response and Amendment dated 12/21/2004
in Reply to Office Action dated 09/21/2004

5. (original)   The method recited in claim 4 wherein the step of locating the second zero space comprises:

locating a third transition, X_3, where value of the input signal is more than a threshold value, V_{THRES}, before the third transition, X_3, but less than the threshold value, V_{THRES}, after the third transition, X_3, the third transition, X_3, being the first such transition following the second transition, X_2; and

locating a fourth transition, X_4, where value of the input signal is less than the threshold value, V_{THRES}, before the fourth transition, X_4, but more than the threshold value, V_{THRES}, after the fourth transition, X_4, the fourth transition, X_4, being the first such transition following the third transition, X_3.

6. (original)   The method recited in claim 5 wherein the step of calculating the bit period comprises determining temporal difference between the third transition, X_3, and the first transition, X_1.

7. (original)   The method recited in claim 1 further comprising displaying the input signal using a multiple of the calculated bit period as the scale.

8. (currently amended)   An apparatus for displaying an input signal, the apparatus comprising:

a processor;

storage connected to the processor, the storage including instructions for the processor to

sample the input signal;

search for a zero space pattern in the sampled signal;

locate a first zero space;

locate a second zero space, following the first zero space;

calculate bit period of the input signal by determining time period between the first zero space and the second zero space; and

display the input signal using the calculated bit period as the basis for a

Application no. 10/027,604
Response and Amendment dated 12/21/2004
in Reply to Office Action dated 09/21/2004

scale; and

wherein each of the zero spaces is a period of time with no signal value above a threshold.

9. (original)   The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to initialize offset and time scale.

10. (original)   The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to determine whether NRZ autoscale is applicable.

11. (original)   The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to:

locate a first transition, X_1, where value of the input signal is more than a threshold value, V_{THRES}, before the first transition, X_1, but less than the threshold value, V_{THRES}, after the first transition, X_1, the first transition, X_1, being the first such transition following the offset; and

locate a second transition, X_2, where value of the input signal is less than the threshold value, V_{THRES}, before the second transition, X_2, but more than the threshold value, V_{THRES}, after the second transition, $X2$, the second transition, X_2, being the first such transition following the first transition, X_1.

12. (original)   The apparatus recited in claim 11 wherein the storage further comprises instructions for the processor to:

locate a third transition, X_3, where value of the input signal is more than a threshold value, V_{THRES}, before the third transition, X_3, but less than the threshold value, V_{THRES}, after the third transition, X_3, the third transition, X_3, being the first such transition following the second transition, X_2; and

locate a fourth transition, X_4, where value of the input signal is less than the threshold value, V_{THRES}, before the fourth transition, X_4, but more than the threshold value, V_{THRES}, after the fourth transition, X_4, the fourth transition, X_4, being the first such

File AG314-037   Attorney Docket 10010654-1

Application no. 10/027,604
Response and Amendment dated 12/21/2004
in Reply to Office Action dated 09/21/2004

transition following the third transition, X_3.

13. (currently amended)   The apparatus recited in claim ~~5~~ <u>8</u> wherein the storage further comprises instructions for the processor to determine temporal difference between the third transition, X_3, and the first transition, X_1.

14. (original) The apparatus recited in claim 13 wherein the storage further comprises instructions for the processor to display the input signal using a multiple of the calculated bit period as the scale.

15. (currently amended)   A machine readable medium comprising program for the machine to display an input signal, the program comprising instructions for the machine to:

    sample the input signal;

    search for a zero space pattern in the sampled signal;

    locate a first zero space;

    locate a second zero space, following the first zero space;

    calculate bit period of the input signal by determining time period between the first zero space and the second zero space; and

        display the input signal using the calculated bit period as the basis for a scale<u>; and</u>

        <u>wherein each of the zero spaces is a period of time with no signal value above a</u>

    <u>threshold</u>.

16. (original) The medium recited in claim 15 wherein the medium is selected from a group consisting of magnetic disc, optical disc, read only memory (ROM), random access memory (RAM), harddrive, compact disc (CD), flash memory, and solid state memory.

//
//
//

File AG314-037

Attorney Docket 10010654-1

Application no. 10/027,604
Response and Amendment dated 12/21/2004
in Reply to Office Action dated 09/21/2004

INTERVIEW SUMMARY

A.   Application number: 10/027,604

B.   Applicant: Chenjing Fernando

C.   Examiner: LEE, Hwa C.

D.   Interview date: December 15, 2004

E.   Interview type: Telephonic

F.   Participants: LEE, Hwa C., examiner

Chung, D. James, Attorney

G.   Exhibits shown or demonstrated: None

H.   Claims discussed: All, in general

I.   Prior art References discussed: None, in particular

J.   Agreements reached:

Claims allowable over the currently cited references as amended herein.

K.   Signature of the examiner: not available to the applicant.

L.   No other PTO personnel were present.

File AG314-037   Attorney Docket 10010654-1